


Industrial Design, Low Power Consumption, High Reliability

InDTU324 Series

Industrial Cellular Modem



The InDTU324 series industrial grade wireless data terminal uses cellular network as the bearer network to provide wireless data transmission channel over TCP/IP. It functionally completes wireless data communications between remote control station serial devices and the central control system, to enable remote control of industrial field sites.

The InDTU324 series is small in size, operates between -40°C \sim 70°C and supports +5 \sim 35V DC wide voltage input, can provide stable data transmission channels for unattended industrial sites.

The product supports various configuration and management methods including PC configuration tool, RTool remote management tool and InHand Device Manager cloud, simplifying on-site deployment and maintenance work, greatly improving deployment efficiency and reducing overall system operation cost, so that customers can really experience the convenience of wireless communication.

The InDTU324 series products are particularly suitable for data acquisition and monitoring of distributed unattended field devices, such as:

- Power distribution automation
- Power meter reading
- Street light monitoring
- Smart water
- Heating system monitoring
- Environmental monitoring
- Meteorological monitoring

Application Case



Features and Advantages

- + Long proven in large-scale applications
- + 4G/3G/GPRS cellular networks
- + Fully industrial-grade, ready for challenging environments
- Hardware and software watchdog and multi-layer link detection mechanism, ensures high divide availability and reliability
- + Support for multiple management gadgets and the InHand Device Manager cloud platform for flexible and efficient on-site or remote network management
- + Support for industrial protocol conversion to help users solve interconnection issues

• Fully industrial-grade, ready for challenging industrial environments

Fully industrial-grade chip, operating temperature as wide as -40° C $\sim 70^{\circ}$ C, supports $+5 \sim 35$ VDC wide voltage power input, protection rating up to IP30, to provide reliable network communications for electric power, industrial and other unattended sites.

Ultra low power consumption, adaptable to various field power supply modes.

• High-reliability design, ensure continuity of data transmission

Self-recovery: embedded watchdog, self recover from faults, ensuring normal operation of the device.

Link redundancy: SMS and IP link mutual backup to ensure continuous data transmission.

Link detection: multi-layer link detection mechanisms including PPP layer heartbeat, ICMP detection, TCP Keep alive and application layer heartbeat, keeping wireless connection "always on".

Efficient to manage, flexible and easy to use

Support for configuration software login or AT command(AT MODE only) via local serial port.

Support for RTOOL remote configuration over TCP/IP.

Configuration via SMS.

Support for remote batch management by Device Manager cloud platform.

• Feature-rich, to provide users with intelligent solutions


Support for transparent TCP/UDP protocol.

Support for InHand DC protocol.

Support for Modbus RTU/Modbus TCP protocol conversion.

Dimensions (mm)

LxWxH=75x46x20mm





Interfaces

Pin	Name	Description				
R\$232 PIN						
1	GPO	General GPIO (DO), on/offline indicator of DTU				
2	RXI	Serial port 1 data receiving				
3	TX1	Serial port 1 data transmitting				
4	TX2	Serial port 2 data transmitting				
5	OFF	Power control: off at high electrical level (3.0-10V), on at low level (0-0.3V) or suspended				
6	RX2	Serial port 2 data receiving				
7	GPI	General GPIO (DI), reserved (Do not recommend to connect.)				
8-9	GND	Ground				
10	V+	Positive				
		RS485 PIN				
1	GPO	General GPIO (DO), on/offline indicator of DTU				
2	B(-)	Serial port 1 RS485-				
3	A(+)	Serial port 1 RS485+				
4	TX2	Serial port 2 data transmitting				
5	OFF	Power control: off at high electrical level (3.0-10V), on at low electrical level (0-0.3V) or when suspended				
6	RX2	Serial port 2 data receiving				
7	GPI	General GPIO (DI), reserved (Do not recommend to connect.)				
8-9	GND	Ground				
10	V+	Positive				



Product Specifications

InDTU324 Hardw	are opecification	15						
Interfaces	ı							
	2 x Logic serial ports: Serial port 1: RS-232/RS-485 (Optional) Serial port 2: RS-232							
Industrial Serial Port	RS-232 signal: TXD, RXD, GND RS-485 signal: 485+, 485-, GND							
	10PIN industrial terminal, 3.5mm pitch							
SIM Card Slot	1,8V/3V, drawer-type slot, dual nano-SIM(Optional)							
Antenna	50Ω / SMA x 1	50Ω / SMA x 1						
Mechanical Prope	erties							
Installation	Wall-mounting		Protection Rating		IP30			
Housing	Metal		Cooling		Fanless			
Power Supply					·			
Power Input	DC5-35V		Polarity Reverse Protection		Support			
Power Interface	Pluggable industrial terminal connection		Overload Protection		Support			
		Standby	Working	Starting	Peak			
Consumption (@12V)	InDTU324L	12mA	47mA	202mA	202mA			
	InDTU324N	16mA	25mA	163mA	163mA			
Ambient Tempera	ature and Humid	ity						
Working Temperature	-40 ~ +70°C		Ambient Humidity		5 ~ 95% (non- condensing)			
Storage Temperature	e -40 ~ +85°C				·			
LED Indicators								
LED	POWER, SIM,	STATUS						
EMC Index								
Static	EN61000-4-2,	level 2						
Surge	EN61000-4-5,	level 2						
Shock Wave Immunity	EN61000-4-12, level 2							
Certification								
CE								

InDTU324 Software Specifications							
Network Connection							
Network Access	APN, VPDN						
Access Authentication	CHAP/PAP						
Network Type	GPRS/3G/4G						
Network Protocol							
Network Protocol	Ping, DNS, transparent TCP/UDP, InHand DC TCP/DC UDP, user-defined login/heartbeat data packet						
Protocol Conversion	Modbus RTU/TCP protocol conversion						
Network Security							
Multi-level Authorization	User levels: administrator, maintenance staff						
Certification Security	Supports login security certification						
Reliability							
Reliable Upgrade	Patent upgrade mechanism, ensures reliable upgrade						
Link Connection Detection	Sends heartbeat packet detection, auto connect once disconnected						
Embedded Watchdog	Device operation self-detection technology, and self-recovery from operation faults						
Network Management							
Configuration Method	Local serial port, RTool, InHand Device Manager, SMS						
Configuration Backup	Supports import and export of configuration files						
Upgrade Method	Patent upgrade mechanism, upgrade firmware through local serial port or remotely						
Log	Supports local and online viewing of logs, facilitates checking device operating status						
Dial-on-Demand	Data activation, timed on/off, SMS activation, phone activation						
Network Management	Supports InHand Device Manager remote central management						



Ordering Guide

	Model code: InDTU324- <wmnn><s><d></d></s></wmnn>								
<wmnn>: Cellular Type & Module</wmnn>	<s>: Serial Port Type</s>	:AT/DATA	<d>:SIM</d>						
Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8	RS232	DATA MODE	SINGLE						
Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8	RS232	AT MODE	SINGLE						
Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8	RS485	DATA MODE	SINGLE						
Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8	RS485	AT MODE	SINGLE						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS232	DATA MODE	SINGLE						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS232	AT MODE	SINGLE						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS485	DATA MODE	SINGLE						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS485	AT MODE	SINGLE						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS232	DATA MODE	DUAL						
Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz	RS485	DATA MODE	DUAL						
	Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD:B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD:B39 (for Cat M1 only)	Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 GSM: B3/B8 Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B3/B3/B4/B5/B8/B1/B1/B1/B1/B2/B2/B2/B28 LTE FDD: B1/B2/B3/B4/B5/B8/B1/B1/B1/B1/B1/B2/B2/B2/B2/B2/B1/B1/B1/B1/B1/B1/B1/B1/B1/B1/B1/B1/B1/	Europe and Asia Pacific - LTE CAT4: LTE FDD. 81/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - LTE CAT4: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B3/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B1/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B26/B28 LTE TDD: B39 (for Cat M1 only) EGPRS:850/900/1800/1900MHz Europe and Asia Pacific - Cat M1/Cat NB1/EGPRS: LTE FDD: B3/B2/B3/B4/B5/B8/B12/B13/B18/B19/B20/B20/B26/B28 LTE TDD						

About Us

InHand Networks is a global leader of Industrial IoT, with a record of tremendous success following groundbreaking innovation since our inception in 2001.

InHand serves world-class partners and customers with industrial M2M routers, gateways, industrial Ethernet switches, rugged computers and IoT management platforms. We provide IoT solutions for various vertical markets including Smart Grid, Industrial Automation, Remote Machine Monitoring, Smart Vending, Smart City, Retail and more.

Proudly bearing the marks of both Rockwell Automation Encompass Product Partner in Asia-Pacific and Schneider Electric CAPP Technology Partner, InHand Networks defines industrial innovation and reliability.



3900 Jermantown Rd., Suite 150, Fairfax, VA 22030 USA T: +1 (703) 348-2988 E: info@inhandnetworks.com www.inhandnetworks.com